


Built-In Motion Detection

- Long-lasting LED floodlight with auto-on sensor
- No-wire installation works directly with existing fixtures
- Wide-angle sensor detects motion within 25 feet
- Illuminates for 90 seconds after detecting movement

Outdoor Security with Indoor Convenience

Enjoy the confidence of an automatic security light without rewiring your fixtures. Smartsense offers long-lasting, bright white LED light with an integrated motion detector — available in three standard sizes for hands-free lighting throughout your home.





Technical Data

Smartsense PAR38 G2

SKU: SSPAR38ND830G2, SSPAR38ND850G2

- Lumen: 1300 Lumen
- Supply Voltage: 120VAC 60Hz
- Power wattage: 15W@ power on, 0.2W@Standby
- Color temperature: 3000/5000K
- Non-Dimmable
- Sensor Type: Pyroelectric Infrared Sensor, photosensitive sensor
- Base Type: E26
- Beam Angle: 40°
- Motion Sensor Angle: 100°
- CRI: >80, PF>0.9
- Life time: 25000hrs



*With light sensor


*Bulb supports "Always On" mode

*Can set the time length of light remains on after motion is detected (1, 2, 4 or 8 minutes).

Smartsense PAR38

- SKU: SS-PAR38NAE26W
- Lumen: 1050 Lumen
- Supply Voltage: 120VAC 60Hz
- Power wattage: 11.5W@power on, 0.2W@Standby
- Color temperature: 3000K
- Non-Dimmable
- Sensor Type: Pyroelectric Infrared Sensor
- Base Type: E26
- Beam Angle: 40°
- Motion Sensor Angle: 100°
- CRI: >80, PF>0.9
- Switching cycles: 100000 cycles, 30S ON/OFF
- Life time: 25000hrs
- Lumen maintenance end of the life time: >70%





Smartsense A19

- SKU: SSA19ND827, SSA19ND850
- Lumen: 800lm
- Supply Voltage: 120VAC 60Hz
- Power wattage: 9.5W@power on, 0.2W@Standby
- Color temperature: 2700/5000K
- Non-Dimmable
- Sensor Type: Pyroelectric Infrared Sensor
- Base Type: E26
- Beam angle: 200°
- CRI: >80, PF>0.9
- Switching cycles: 100000 cycles, 30S ON/OFF
- Life time: 25000hrs
- Lumen maintenance end of the life time: >70%



*Bulb supports "Always On" mode

Smartsense BR30

- SKU: SSBR30ND827, SSBR30ND850
- Lumen: 650 Lumen
- Supply Voltage: 120VAC 60Hz
- Power wattage: 8.5W@power on, 0.2W@Standby
- Color temperature: 2700/5000K
- Non-Dimmable
- Sensor Type: Pyroelectric Infrared Sensor
- Base Type: E26
- Beam angle: 110°
- CRI: >80, PF>0.9
- Switching cycles: 100000 cycles, 30S ON/OFF
- Life time: 25000hrs
- Lumen maintenance end of the life time: >70%



*Bulb supports "Always On" mode